


UPS SYSTEMS:

ES CONVERSION KIT

UPS SYSTEM FOR 230Vac DEVICES OR LAMPS UP TO 25W



COSINE DEVELOPMENTS
LEADERS IN EMERGENCY LIGHTING

DESCRIPTION

The ES Conversion Kit provides 1-hour emergency backup for 230Vac loads up to 25W. It is housed in a durable plastic enclosure with end caps, ensuring safe and easy installation. The unit features an integrated Li-ion battery built directly into the enclosure. This all-in-one design eliminates the need for a separate remote battery box.



TECHNICAL DATA

BATTERY DISCHARGE CURRENT	2A
BATTERY TYPE	11.1V Li-ion
CHARGING TIME	6 hours
CHARGING INDICATION	Provided
DIMENSIONS	215 x 42 x 28mm
EMERGENCY LIGHTING DURATION	1 hour
LAMP TYPE	Any ES, LED lamps or loads up to 25W
MAINS POWER CONSUMPTION	10VA
MAINS VOLTAGE	100 - 253Vac 50/60Hz
MAXIMUM AMBIENT TEMPERATURE	+45°C

FEATURES

- > Emergency kit for 230Vac lamps up to 25W
- > Polycarbonate enclosure with end caps
- > Maintained or non-maintained
- > Emergency lighting for 1 hour
- > 2 year warranty on inverter



The ES Conversion Kit
Complies with SANS 1464-22

